



# RM SERIES



**RMM2050 Model Includes:**

- 2 Watt MURS provides coverage of up to 220,000 Sq. Ft./13 floors
- 5 Channels Operation
- Operate on 5 MURS (unlicensed) Frequencies
- 219 PL/DPL codes, including 6 customizable codes
- Channel Announcement with Voice Alias
- Meet Military 810 C, D, E, F, G and IP54/55 specifications
- Antimicrobial Protection
- Two programmable buttons\* give quick one-touch access to features
- Single-unit drop-in charger provides charging and battery level status via tri-color LED
- Easy Cloning with Single-Unit Charger Cloning Cable or Multi-Unit Charger (sold separately)
- Weighing 8.6 ounces with the battery
- 2 Pin Accessory Plug

**Inside the Box:**

- RMM2050 radio
- 2100 mAh 3.7V Lithium Ion Rechargeable Battery
- Standard Drop-In Charging Tray w/ Wall Adaptor
- Swivel Belt Holster With 3.5" Spring Clip
- Quick Reference Leaflet
- RF Safety Booklet

\* Advanced features via customer programming software (CPS)

Display Number	Freq. (MHz)	Bandwidth
1	154.5700	25 KHz only
2	154.6000	25 KHz only
3	151.8200	12.5 KHz only
4	151.8800	12.5 KHz only
5	151.9400	12.5 KHz only

Note: Refer to User's Guide for more detail. New users must license frequencies.

Country of Origin	Radio Dimensions	Radio Weight w/batt.	Box Dimensions	Box Weight w/radio	Overpack Box Dimensions	Overpack Weight w/radios
Malaysia	7.38 x 2.25 x 1.5	0.33	10.08 X 6.69 X 2.4	1.23	13.75 x 11.25 x 7.13	8.25

All dimensions are approximate, in inches (HxWxD) and lbs., overpack contains six (6) radios.

**RMM2050**

POWER	CHANNELS	COLOR	MODEL	UPC CODE	MSRP
2W	5	Black	RMM2050BHLAA	7 48091 00028 7	<b>\$225.00</b>

This product may be price protected under Motorola's Minimum Advertised Price (MAP) policy. Please contact your Motorola Account Manager for the current Motorola MAP Policy.